



## Art.-Nr: MNXL104 miniControl XL plus (MNXL) Central battery system Combination cabinet Central battery system, Combination cabinet, 2 pcs. DCM, 1 pcs. LDM, Leuchten

MAX. 32 MAINS CIRCUITS / 1.500 W, 1H / 640 LUMINAIRES

The Low Power System miniControl XL plus closes with a maximum output of 1.500 W the gap between the smaller powered miniControl XL plus and the big brother midiControl plus. Through the principle of decentralization per fire compartment, similar to a single battery system, there will be no costs for E30-powerlines and their installation. The miniControl XL plus is installed in an operating room in each fire compartment.

Batteries are not included and have to be ordered separately.



More information

## **TECHNICAL DATA**

| Inserts                    | 17 pcs.    |
|----------------------------|------------|
| no-trans-Anzahl DCM Module | 2 pcs.     |
| Number of circuits         | 4          |
| Loader                     | Yes        |
| no-trans-Anzahl Lademodule | 1 pcs.     |
| Modules SAM                | Yes        |
| IO modules                 | Yes        |
| CCIF                       | Yes        |
| Connectable                | Yes        |
| Outgoing UPS               | No         |
| Battery compartment        | Yes        |
| Supply power 1 h           | 2575 W     |
| Supply power 3 h           | 1245 W     |
| Supply power 8 h           | 570 W      |
| Input voltageAC            | 230 V      |
| Input frequency            | 50 / 60 Hz |
| Output voltage AC          | 230 V      |



| Material              | Steel sheet |
|-----------------------|-------------|
| Housing color         | RAL 7035    |
| Insulation class      | IP20        |
| Insulation class      | IP20        |
| Depth                 | 230 mm      |
| Width                 | 571 mm      |
| Height                | 1470 mm     |
| Weight                | 49.8 kg     |
| Weight                | 49.8        |
| Customs tariff number | 85371098    |

As of: 11.07.2024 - Subject to technical changes and errors.