



**Art.-Nr: YMOBM-RE-SWISSPIR-BAT**  
**CASAMBI® motion detector Swisspir**  
**LIGA air,**

CASAMBI® motion detectors consist of integrated CASAMBI® technology and make it possible to control luminaires without wiring work. Use the CASAMBI® app to configure parameters such as brightness and automatically switching on and off at dusk or movement. This can result in savings of up to 90%. The sensors are available in various designs for ceiling mounting or recessed installation and various detection zones from 5 to 28 m.



Mer informasjon



TEKNISKE DATA

<b>Dimensjoner</b>	
diameter	25 mm
Produktmål høyde	48 mm
Produktvekt	0.07 kg
<b>Farge</b>	
Farge	Hvit
<b>Koffertmateriale</b>	
Koffertmateriale	plast
<b>Sertifisering</b>	
Sertifisering	CE
IP-beskyttelse)	IP44
<b>Oppbevaringstemperaturområde</b>	
Oppbevaringstemperaturområde (min)	-25 °C
Lagringstemperaturområde (maks.)	+65 °C
<b>temperaturer</b>	
Omgivelsestemperatur (min)	-20 °C
Omgivelsestemperatur (maks.)	+50 °C
<b>CASAMBI kontaktinformasjon management</b>	
Type kommunikasjon	blåtann
Maks. sendeeffekt	+4 dBm
Sensorteknologi	Infrarød



Deteksjonsvinkel	100 °
Sensor rekkevidde	7 m
<b>Monteringstype</b>	
Monteringstype	Takmontering

stand: 21.06.2024 - Det tas forbehold om tekniske endringer og feil.