



Art.-Nr: YMOCA-DAMA-MINI

NEW! Expected to be available from 01.10.2024

The CASA DAMA Mini Module is a specially designed module for flush mounting, which takes control of up to 15 wired DALI luminaires. This intelligent module allows the DALI luminaires to be wirelessly controlled using advanced Casambi technology. With an integrated DALI bus power supply of 30 mA, the module ensures efficient and reliable connection of the luminaires. Its form factor simplifies installation, while the compact design allows for unobtrusive integration into existing lighting systems. This combination of wireless control and DALI connection makes the CASA DAMA Mini an optimal solution for smart lighting requirements.



Mer informasjon



TEKNISKE DATA

Dimensjoner	
Produktdimensjoner lengde	50 mm
Produktdimensjoner bredde	48 mm
Produktmål høyde	21.6 mm
Emballasjedimensjoner	
Emballasjedimensjoner lengde	60 mm
Emballasjemål bredde	60 mm
Emballasjemål høyde	34 mm
Vekt inkludert emballasje	0.05 kg
Farge	
Farge	Hvit
Koffertmateriale	
Koffertmateriale	plast
Sertifisering	
Sertifisering	CE, RoHS
IP-beskyttelse)	IP20
Oppbevaringstemperaturområde	
Oppbevaringstemperaturområde (min)	-25 °C
Lagringstemperaturområde (maks.)	+75 °C



CS_GROUP.HousingTemperature	
Omgivelsestemperatur (maks.)	60 °C
Elektrisk forbindelse	
Tilkoblingstverrsnitt	1.5 mm ²
Dimming type	DALI
Inngangsspenning AC	220-240V / 50-60Hz V
Standby-forbruk	0.7 W
temperaturer	
Omgivelsestemperatur (min)	-20 °C
Omgivelsestemperatur (maks.)	+50 °C
CASAMBI kontaktinformasjon management	
Type kommunikasjon	DALI 1, DALI 2
Frekvensbånd	2,403 - 2,479 GHz
Maks. sendeeffekt	+4 dBm

stand: 21.06.2024 - Det tas forbehold om tekniske endringer og feil.